

IC 7300 Settings for Digital

VA7FI has the following settings on his radio. The settings in grey are there for reference only and can be different.

Menu > SET > Connectors:		
ACC/USB Output Select		AF
ACC/USB AF Output Level		40%
ACC/USB AF SQL		OFF (Open)
ACC/USB AF Beep Speech... Output		OFF
ACC/USB IF Output level		50%
ACC MOD Level		50%
USB MOD Level		40%
DATA OFF MOD		MIC
DATA MOD		USB
Menu > SET > Connectors > CI-V:		
CI-V Baud Rate		Auto
CI-V Address		note it
CI-V Transceive		ON
CI-V USB→Remote Tx Address		N/A
CI-V Output (for ANT)		OFF
CI-V USB Port		Link to [REMOTE]
Menu > Set > Connectors:		
USB Serial Function		CI-V
Menu > Set > Connectors > USB SEND Keying:		
USB SEND		RTS
USB Keying (CW)		OFF
USB Keying (RTTY)		OFF
Inhibit Timer at USB Connection		ON
Mode	Digital	Voice
Default Frequency	7.078.00 USB-D	3.739.00 LSB
MUT (select and turn the knob)		
RF POWER	30%	100%
MIC GAIN	40%	40%
COMP	N/A	ON 4
MONITOR	ON 100%	OFF 100%
FUNCTION		
P.AMP ATT	OFF	OFF
AGC	OFF	SLOW
NOTCH	OFF	OFF
NB	OFF	ON
NR	OFF	OFF
IP+	OFF	OFF
VOX	OFF	OFF
COMP	N/A	ON
1/4	OFF	WIDE
MONI	ON	OFF