

Field Day Log

This is a quick how-to on how to submit electronic logs for for the 2020 Field Day for those who don't have a logging software.

During the Contest

Use the [Field Day Log Spreadsheet](#) to log your contacts.

- Only enter information in the green cells.
- Information must be formatted as in the example (case is not sensitive):
 - The **Band** can be a general frequency of the band or the exact frequency. Only the general frequency will end up being submitted. HF are in kHz, and VHF/UHF in MHz.
 - The **Mode** can be cw, dg (digital), ph (phone), or fm.
 - The **Date** must be either 6/27 or 6/28 in Zulu time.
 - The **Time** must be in 100's in Zulu time.
 - The **Section Code** must be exact. If an operator uses the name instead of the code (ex. "Georgia"), you can use the "Lookup" tab to find the code.
 - The sections in red are to help and will NOT be copied in the log later.

| A | B | C | D | E | F | G | H | I | J | K | L |
|-------|-----|------|------|----------|----------|----------|-------|----------------------------|-----------------------|------------|------------|
| Band | Mod | Date | Time | Callsign | Category | Sec Code | Notes | Category | Section | Duplicate? | Base Point |
| 1800 | cw | 6/27 | 1800 | VA7AA | 3a | ct | | Portable, 3 ops | Connecticut | | 2 |
| 3500 | CW | 6/27 | 1802 | ve7akk | 4A | EMA | | Portable, 4 ops | Eastern Massachusetts | | 2 |
| 7000 | dg | 6/27 | 1801 | VE7ABL | 5a | me | | Portable, 5 ops | Maine | yes | 2 |
| 14000 | dg | 6/27 | 1803 | VA7AC | 1b | ph | | Portable, 1 op | New Hampshire | | 2 |
| 21000 | ph | 6/27 | 1802 | VA7ACL | 2b | ri | | Portable, 2 ops | Rhode Island | | 1 |
| 28000 | ph | 6/28 | 0100 | VA7AGG | 1c | vt | | Mobile, 1 op | Vermont | | 1 |
| 50 | ph | 6/28 | 0101 | VA3AGN | 1d | wma | | Home Station, 1 op | Western Massachusetts | | 1 |
| 144 | fm | 6/28 | 0102 | VA7AHV | 2d | eny | | Home Station, 2 ops | Eastern New York | | 1 |
| 222 | fm | 6/28 | 0103 | VA7AIB | 1e | nji | | E-Power Home Station, 1 op | NYC / Long Island | | 1 |
| 432 | fm | 6/28 | 0104 | VE7ABL | 4f | nnj | | EOC, 4 ops | Northern New Jersey | yes | 1 |

Calculating Points

Using the Scoring Tab, fill in the multiplier and bonus points using page 4-5 of the [Field Day Packet](#).

| | | | | | |
|--|------------|-------|--|--|--|
| See: Section 7 on p.4 of http://www.arrl.org/files/file/Field-Day/2020/2020%20Field%20Day%20Packet.pdf | | | | | |
| | Actual | Total | | | |
| Power Multiplier (Sec 7.2) | 2 | 5 | | | |
| Bonus Points: | | | | | |
| * 100% Emergency Power (Sec 7.3.1) | 100 | 100 | | | |
| * Media (Sec 7.3.2) | | 100 | | | |
| * Public Location (Sec 7.3.3) | | 100 | | | |
| * Public Information Table (Sec 7.3.4) | | 100 | | | |
| * Formal Message (Sec 7.3.5) | | 100 | | | |
| * Message Handling (Sec 7.3.6) | | 100 | | | |
| * Satellite (Sec 7.3.7) | | 100 | | | |
| * Alternate Power (Sec 7.3.8) | 100 | 100 | | | |
| * W1AW Bulletin (Sec 7.3.9) | | 100 | | | |
| * Educational (Sec 7.3.10) | | 100 | | | |
| * Elected Official Visit (Sec 7.3.11) | | 100 | | | |
| * Agency Visit (Sec 7.3.12) | | 100 | | | |
| * Gota Bonus (Sec 7.3.13) | | 100 | | | |
| * Web Submission (Sec 7.3.14) | 50 | 50 | | | |
| * Youth Participation (Sec 7.3.15) | | 100 | | | |
| * Social Media (Sec 7.3.16) | | 100 | | | |
| * Safety Office (Sec 7.3.17) | | 100 | | | |
| | | | | | |
| | | | | | |
| Sub Total from Contacts | 14 | | | | |
| Contacts x Multipliers | 28 | | | | |
| Total Points | 278 | | | | |

Formatting the Log

Before the log file can be submitted, the information from the spreadsheet must be converted to the proper format. To do that, use the [ARRL Field Day Cabrillo Form](#)

- Fill in your station information:

Submitter's E-mail Address ARRL/RAC Section:

Call Used Operator(s) Call(s) Station Call

Operator Band ALL Mode MIXED Power

Station

Exchange Info:

Category Sent Sec Sent

Variability

Info

Claimed Score Club Name

Operator's Full Name and Address

Patrick Truchon

 Roberts Creek, BC, V0N2W1

* Copy the green sections from the spreadsheet at the bottom of the next screen:

Soapbox: (unlimited length)

QSO Data:

Enter your QSO data in this text area, one QSO per line. Each of the fields below must be entered for each QSO. One or more spaces must separate each item in a QSO. All dates and times must be in UTC. If the time of the QSO is not known, enter 1800.

Band Mode Date Time Call-Copied Category-Copied Sec-Copied

20 cw 6/27 1800 wlaw 3f ct

<-Enter your QSO data starting on the next line. Do not erase this line.->

```
1800 cw 6/27 1800 VA7AA 3a ct
3500 CW 6/27 1802 ve7akk 4A EMA
7000 dg 6/27 1801 VE7ABL 5a me
14000 dg 6/27 1803 VA7AC 1b nh
21000 ph 6/27 1802 VA7ACL 2b ri
28000 ph 6/28 0100 VA7AGG 1c vt
50 ph 6/28 0101 VA3AGN 1d wma
144 fm 6/28 0102 VA7AHV 2d eoy
222 fm 6/28 0103 VA7AIB 1e nli
432 fm 6/28 0104 VE7ABL 4f nni
```